AN13792

如何使能异步中断并唤醒系统

Rev. 1 — 2024年**5**月**27**日

应用笔记

文档信息

信息	内容
关键词	AN13792, RT1180, 唤醒, 异步中断, 低功耗
摘要	本应用笔记将会介绍如何使能异步中断并将进入低功耗状态的芯片唤醒。



如何使能异步中断并唤醒系统

1 介绍

i.MX RT1180 跨界 MCU 系列包括千兆时间敏感网络(TSN)交换机,支持实时丰富的网络集成,可处理时间 敏感和工业实时通信。i.MX RT1180 支持多种协议,桥接实时以太网和 Industry 4.0 系统之间的通信。该系列集 成先进的 EdgeLock 安全区域,基于 800 MHz Cortex-M7 和 240 MHz Cortex-M33 双核架构,可实现设计灵活 性。

低功耗设计同样是 RT1180 的关键功能,本应用笔记将会介绍如何使能异步中断并将进入低功耗状态的芯片唤醒。

2 同步中断和异步中断

本应用笔记中将同步中断和异步中断定义为:

- 同步中断:当 bus clock 使能时产生的中断,后续将会使用 Sync interrupt 作为同步中断的缩写。
- •异步中断:当 bus clock 关闭时产生的中断,后续将会使用 Async interrupt 作为异步中断的缩写。

Bus Clock				Sync	Interrupt
Function C	lock	Modu	le A	Asyr	nc Interrupt
Bus Clock	Func	tion Clock	Sync Inter	rupt	Async Interrupt
Enabled	E	Enabled	Y		
Disabled	E	Enabled	N		Y

图 1是时钟与中断关系的示意图。当进入一些低功耗状态时,系统的 bus clock 将会停止工作以更加节省功耗。此时,因为 bus clock 停止工作,同步中断无法产生,进而无法作为唤醒源唤醒系统。与此同时,需要注意的是当系统进入低功耗状态时产生中断的模块(例如各种外设,Timer, GPT, GPIO, LPSPI等)的供电需要保持。

很多外设都支持产生异步中断,用户可以参考用户手册中的中断章节获取具体哪些外设支持异步中断功能。

表 1. 部分支持异步中断的外设

19	LPUART1	OR	TX interrupt
19	-	OR	Async TX interrupt
19	-	OR	RX interrupt
19		OR	Async RX interrupt
57	GPIO2	OR	Interrupt 0
57		OR	Async interrupt 0

3 使能异步中断

当bus clock 始终关闭时异步中断不会自动被使能,用户需要通过配置寄存器的方法使能异步中断。通常在进入 一个低功耗状态前需要使用握手功能(handshake),handshake的目的是保证在CPU发出低功耗指令WFI之 前,所有外设完成所有传输,不再接收新的传输,从而安全进入低功耗。当握手完成后,异步中断功能自动使 能。

在RT1180或者RT1170这样的多核系统中,如果一个外设没有被分配到一个域里,那么需要2个寄存器来完成 握手。stop_req需要从CM33域内的GPR_SHARED8 和GPR_SHARED9以及 CM7域内的GPR_SHARED12 和GPR_SHARED13中发送出来,这时停止接收信号(stop_ack)才能被确认。



1				
	А	В	С	D
	0	0	0	0
	0	1	0	0
	1	0	0	0
	1	1	1	1

A: CAN1_STOP_REQ from GPR_SHARED8

B: CAN1_STOP_REQ from GPR_SHARED12

C: CAN1_STOP_ACK from GPR_SHARED_STATUS1

D: CAN1_STOP_ACK from GPR_SHARED_STATUS5

图 2. Handshake

以 CAN1作为示例, CAN1_STOP_REQ 需要分别从 GPR_SHARED8 bit[24] 和 GPR_SHARED12 bit[24]发送:

```
CCM->GPR_SHARED_CTRL[8].GPR_SHARED |= 1<<24;
CCM->GPR_SHARED_CTRL[12].GPR_SHARED |= 1<<24;
```

接着检查传输是否完成,通过检查 GPR_SHARED_STATUS1 bit[3] 和 GPR_SHARED_STATUS5 bit[3] 即可获知状态:

while((CCM->GPR_SHARED_STATUS[1] & 0x8) == 0); //Check bit3
while((CCM->GPR_SHARED_STATUS[5] & 0x8) == 0); //Check bit3

如果一个外设被指定到一个域,那么只需要发送一个stop_request。同样以CAN1为例,假定它被分派 到CM33域, CAN1 STOP REQ 只需要从 GPR SHARED8 bit[24]发送即可:

CCM->GPR SHARED CTRL[8].GPR SHARED |= 1<<24;

接着通过检查 GPR SHARED STATUS1 bit[3] 来检查传输是否结束:

while((CCM->GPR SHARED STATUS[1] & 0x8) == 0); //Check bit3

在进入低功耗模式之前,请确保所有的外设都完成了传输。除此之外,对于握手的序列需要注意的是,DMA/ENET(Bus Master)需要首先完成握手,然后才是 Flash/内存(Bus Slave)。

如何使能异步中断并唤醒系统

4 例子: 使能 GPIO 的异步中断

下面将会使用 RT1180 中的 RGPIO4 演示如何使能一个 GPIO 的异步中断功能。当 RT1180 进入系统睡眠状态(system sleep)时,bus clock 被关闭系统所有的 bus 总线会停止工作。此时异步中断将被作为可用的系统唤醒源将芯片从系统睡眠状态唤醒。在配置好 GPIO 的中断功能后(与普通的中断一样),用户需要参考下面的代码以使能异步中断。但是请注意,当握手步骤完成后,GPIO 的寄存器不能被 CPU 读写。正是基于这点,通常建议将握手的步骤放置在 WFI 指令之前完成。

```
void gpio_async_config()
{
    CCM->GPR_SHARED_CTRL[8].GPR_SHARED |= 1<<19;
    CCM->GPR_SHARED_CTRL[12].GPR_SHARED |= 1<<19;
    while((CCM->GPR_SHARED_STATUS[0] & (1<<19)) == 0); //Check bit19
    while((CCM->GPR_SHARED_STATUS[4] & (1<<19)) == 0); //Check bit19
}</pre>
```

当系统被 GPIO 唤醒后,用户需要清除 GPIO 中断的标志位,正如前文所述,当握手完成后,CPU 不能读写 GPIO 的寄存器。因此,在清除 GPIO 中断标志位前,用户需要取消握手,让 GPIO 的状态从 stop 状态恢复到 run 状态。可以参考以下代码。

```
void GPI04_0_IRQHandler()
{
    CCM->GPR_SHARED_CTRL[8].GPR_SHARED &= ~(1<<19);//Cancel handshake first
    CCM->GPR_SHARED_CTRL[12].GPR_SHARED &= ~(1<<19); //Cancel handshake first
    RGPI0_ClearPinsInterruptFlags(RGPI04, 0, 1 <<16); //Clean the interrupt flag
    SDK_ISR_EXIT_BARRIER;
}</pre>
```

5 Note about the source code in the document

Example code shown in this document has the following copyright and BSD-3-Clause license:

Copyright 2024 NXP Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

- 1. Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
- 2. Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials must be provided with the distribution.
- 3. Neither the name of the copyright holder nor the names of its contributors may be used to endorse or promote products derived from this software without specific prior written permission.

THIS SOFTWARE IS PROVIDED BY THE COPYRIGHT HOLDERS AND CONTRIBUTORS "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE COPYRIGHT HOLDER OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

AN13792_ZH	All information provided in this document is subject to legal disclaimers.	© 2024 NXP B.V. All rights reserved.
应用笔记	Rev. 1 — 2024 年5月 27 日	

6 修订记录

<u>表2</u>汇总了自初始版以来对本文档所做的更改。

表 2. 修订记录

文档号	日期	说明
AN13792_ZH v.1	2024 年 5 月 27 日	初次发布

如何使能异步中断并唤醒系统

Legal information

Definitions

Draft — A draft status on a document indicates that the content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included in a draft version of a document and shall have no liability for the consequences of use of such information.

Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. NXP Semiconductors takes no responsibility for the content in this document if provided by an information source outside of NXP Semiconductors.

In no event shall NXP Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, NXP Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms and conditions of commercial sale of NXP Semiconductors.

Right to make changes — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — NXP Semiconductors products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of an NXP Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. NXP Semiconductors and its suppliers accept no liability for inclusion and/or use of NXP Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using NXP Semiconductors products, and NXP Semiconductors accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the NXP Semiconductors product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

NXP Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using NXP Semiconductors products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). NXP does not accept any liability in this respect.

Terms and conditions of commercial sale — NXP Semiconductors products are sold subject to the general terms and conditions of commercial sale, as published at https://www.nxp.com/profile/terms, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. NXP Semiconductors hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of NXP Semiconductors products by customer.

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

Suitability for use in non-automotive qualified products — Unless this document expressly states that this specific NXP Semiconductors product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. NXP Semiconductors accepts no liability for inclusion and/or use of non-automotive qualified products in automotive equipment or applications.

In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without NXP Semiconductors' warranty of the product for such automotive applications, use and specifications, and (b) whenever customer uses the product for automotive applications beyond NXP Semiconductors' specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies NXP Semiconductors for any liability, damages or failed product claims resulting from customer design and use of the product for automotive applications beyond NXP Semiconductors' standard warranty and NXP Semiconductors' product specifications.

Translations — A non-English (translated) version of a document, including the legal information in that document, is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

Security — Customer understands that all NXP products may be subject to unidentified vulnerabilities or may support established security standards or specifications with known limitations. Customer is responsible for the design and operation of its applications and products throughout their lifecycles to reduce the effect of these vulnerabilities on customer's applications and products. Customer's responsibility also extends to other open and/or proprietary technologies supported by NXP products for use in customer's applications. NXP accepts no liability for any vulnerability. Customer should regularly check security updates from NXP and follow up appropriately. Customer shall select products with security features that best meet rules, regulations, and standards of the intended application and make the ultimate design decisions regarding its products and is solely responsible for compliance with all legal, regulatory, and security related requirements concerning its products, regardless of any information or support that may be provided by NXP.

NXP has a Product Security Incident Response Team (PSIRT) (reachable at <u>PSIRT@nxp.com</u>) that manages the investigation, reporting, and solution release to security vulnerabilities of NXP products.

 $\ensuremath{\mathsf{NXP}}\xspace \mathsf{B.V.}$ — NXP B.V. is not an operating company and it does not distribute or sell products.

Trademarks

Notice: All referenced brands, product names, service names, and trademarks are the property of their respective owners. **NXP** — wordmark and logo are trademarks of NXP B.V.

AN13792

如何使能异步中断并唤醒系统

EdgeLock — is a trademark of NXP B.V.

AMBA, Arm, Arm7, Arm7TDMI, Arm9, Arm11, Artisan, big.LITTLE, Cordio, CoreLink, CoreSight, Cortex, DesignStart, DynamIQ, Jazelle, Keil, Mali, Mbed, Mbed Enabled, NEON, POP, RealView, SecurCore, Socrates, Thumb, TrustZone, ULINK, ULINK2, ULINK-ME, ULINK-PLUS, ULINKpro, µVision, Versatile — are trademarks and/or registered trademarks of Arm Limited (or its subsidiaries or affiliates) in the US and/or elsewhere. The related technology may be protected by any or all of patents, copyrights, designs and trade secrets. All rights reserved.

NXP Semiconductors

AN13792

如何使能异步中断并唤醒系统

内容

	-
1 介绍	2
2 同步中断和异步中断	2
3 使能异步中断	
4 例子: 使能 GPIO 的异步中断	4
5 Note about the source code in the	
document	4
6 修订记录	5
Legal information	6

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.

© 2024 NXP B.V.

All rights reserved.

For more information, please visit: https://www.nxp.com

Date of release: 2024年5月27日 Document identifier: AN13792_ZH